

(12) INTERNATIONAL APPLICATION PUBLISHED UNDER THE PATENT COOPERATION TREATY (PCT)

(19) World Intellectual Property
Organization
International Bureau



(43) International Publication Date
8 April 2004 (08.04.2004)


PCT

(10) International Publication Number
WO 2004/029594 A1

- (51) International Patent Classification⁷: G01N 21/37, G01J 5/42
- (21) International Application Number: PCT/FI2003/000684
- (22) International Filing Date: 19 September 2003 (19.09.2003)
- (25) Filing Language: Finnish
- (26) Publication Language: English
- (30) Priority Data: 20021733 30 September 2002 (30.09.2002) FI
- (71) Applicant (for all designated States except US): NOVEL-TECH SOLUTIONS LTD [FI/FI]; Kyypellontie 1, FIN-21350 Ilmarinen (FI).
- (72) Inventor; and
- (75) Inventor/Applicant (for US only): KAUPPINEN, Jyrki [FI/FI]; Kyypellontie 1, FIN-21350 Ilmarinen (FI).
- (74) Agent: TURUN PATENTTITOIMISTO OY; P.O. Box 99, FIN-20521 Turku (FI).
- (81) Designated States (national): AE, AG, AL, AM, AT (utility model), AT, AU, AZ, BA, BB, BG, BR, BY, BZ, CA, CH, CN, CO, CR, CU, CZ (utility model), CZ, DE (utility model), DE, DK (utility model), DK, DM, DZ, EC, EE (utility model), EE, EG, ES, FI (utility model), FI, GB, GD, GE, GH, GM, HR, HU, ID, IL, IN, IS, JP, KE, KG, KP, KR, KZ, LC, LK, LR, LS, LT, LU, LV, MA, MD, MG, MK, MN, MW, MX, MZ, NI, NO, NZ, OM, PG, PH, PL, PT (utility model), PT, RO, RU, SC, SD, SE, SG, SK (utility model), SK, SL, SY, TJ, TM, TN, TR, TT, TZ, UA, UG, US, UZ, VC, VN, YU, ZA, ZM, ZW.
- (84) Designated States (regional): ARIPO utility model (GH), ARIPO patent (GH), ARIPO utility model (GM), ARIPO patent (GM), ARIPO utility model (KE), ARIPO patent (KE), ARIPO utility model (LS), ARIPO patent (LS), ARIPO utility model (MW), ARIPO patent (MW), ARIPO utility model (MZ), ARIPO patent (MZ), ARIPO utility model (SD), ARIPO patent (SD), ARIPO utility model (SL), ARIPO patent (SL), ARIPO utility model (SZ), ARIPO patent (SZ), ARIPO utility model (TZ), ARIPO patent (TZ), ARIPO utility model (UG), ARIPO patent (UG), ARIPO utility model (ZM), ARIPO patent (ZM).

[Continued on next page]

(54) Title: PHOTOACOUSTIC DETECTOR



(57) Abstract: The invention relates to a photoacoustic detector, comprising at least a first chamber (V_0) suppliable with a gas to be analyzed, a window for letting modulated and/or pulsed infrared radiation and/or light in the first chamber (V_0), and means for detecting pressure variations created in the first chamber by absorbed infrared radiation and/or light. The means for detecting pressure variations created in the first chamber by absorbed infrared radiation and/or light comprise at least an aperture provided in the wall of the first chamber (V_0), in communication with which is provided a door arranged to be movable in response to the movement of a gas, and means for a contactless measurement of the door movement. The invention relates also to a sensor for a photoacoustic detector and to a method in the optimization of a door used as a sensor for a photoacoustic detector.

WO 2004/029594 A1



ARIPO utility model (ZW), ARIPO patent (ZW), Eurasian patent (AM, AZ, BY, KG, KZ, MD, RU, TJ, TM), European patent (AT, BE, BG, CH, CY, CZ, DE, DK, EE, ES, FI, FR, GB, GR, HU, IE, IT, LU, MC, NL, PT, RO, SE, SI, SK, TR), OAPI patent (BF, BJ, CF, CG, CI, CM, GA, GN, GQ, GW, ML, MR, NE, SN, TD, TG).

— *before the expiration of the time limit for amending the claims and to be republished in the event of receipt of amendments*

Published:

— *with international search report*

For two-letter codes and other abbreviations, refer to the "Guidance Notes on Codes and Abbreviations" appearing at the beginning of each regular issue of the PCT Gazette.

Photoacoustic detector

The invention relates to a photoacoustic detector as set forth in the preambles of the appended independent claims, and to a sensor for a photoacoustic detector as well as to a method in the optimization of a door used as a sensor for a photoacoustic detector.

When infrared radiation or light in general falls on a gas-filled chamber containing a gas to be analyzed at a partial pressure p_x and a carrier gas at a partial pressure p_N (often typically nitrogen), radiation will be absorbed by the gas p_x . After the absorption process, energy converts to thermal movement at a certain time constant τ (e.g. 10^{-5} s). Thus, temperature of the total gas increases by ΔT per unit time. The increase of temperature results also in a pressure increase Δp .

A typical photoacoustic detector comprises a chamber, which is suppliable with a gas to be analyzed, a window for letting modulated or pulsed infrared radiation or light in the chamber, and a pressure sensor adapted to measure pressure variations produced by absorbed infrared radiation or light in the chamber. The pressure sensor comprises typically a microphone, a thin Mylar or metal film. A photoacoustic detector can be used for measuring or detecting infrared radiation in general, but one specific and important application of a detector deals with the measurement and detection of gases or gas mixtures regarding for example air quality and pollution.

In microphones, the movement of a film (Mylar) is usually measured capacitively. The Mylar film is coated with metal and placed in the proximity of another solid metal diaphragm. The result is a capacitor, having a capacitance

$$C = \frac{\epsilon_r \epsilon_0 A}{h}, \quad (a)$$

where h represents a distance between the films at rest, A is a surface area of the films, $\epsilon_r \epsilon_0$ is a dielectric constant for a gas present between the sheets and ϵ_0 the same for a vacuum. The measurement of C provides h which gives the movement of a Mylar film, because

$$\Delta C = -\frac{\epsilon_r \epsilon_0 A}{3h^2} \Delta h, \quad (b)$$

where Δh is a change of distance in the middle and $\Delta h/3$ is an average change of distance. Further

$$\frac{\Delta C}{C} = -\frac{\Delta h}{h} \quad (c)$$

or

$$|\Delta h_{\min}| \approx \frac{h}{C/\Delta C} = \frac{h}{S/N}, \quad (d)$$

where S/N is a signal-to-noise ratio in measuring electronics.

5 Capacity measurements of the prior art are limited by a gas flow present between the sheets, as h changes. As the gap h decreases, the gas is forced to flow out from between the sheets and return when h is increasing. The flow has inertia and that requires energy. A result of this is that, the higher the angular oscillation frequency ω of a diaphragm and the smaller h , the more the flow decreases the amplitude of a
10 diaphragm movement. Thus, h cannot be decreased infinitely, as this would augment a signal ΔC . Therefore, the commercially available microphones function at the limits of physical laws and their responsivity cannot be improved in that regard.

In their publication [1], Nicolas Lederman et al. disclose a photoacoustic detector
15 for a sensor, wherein the sensor is fabricated from a cantilever type film, which responses to the movement of a gas in the chamber of a photoacoustic detector and in which film is integrated a piezoelectric element registering the cantilever movement. A problem with the sensor set forth in the publication is that the cantilever's resonance frequency has been omitted. It is likely that a piezoelectric
20 element attached to a sensor increases the sensor's resonance frequency and thus deteriorates the sensor's response. The sensor presented in the publication is quite inaccurate and, therefore, not suitable for high precision applications. Neither does the publication say anything about optimization of a chamber and a sensor in the photoacoustic detector, i.e. the ratio of the size of a chamber to that of a sensor.

25 In their publications [2] and [3], M.H. de Paula et al. also disclose an alternative to a traditional diaphragm solution. The publications propose that a pellicle be fitted over a small duct in a photoacoustic detector cell at a distance of about 0,1 mm from the duct. According to what is stated in the publication, the pellicle is not provided
30 with a so-called rim around itself, the pellicle thus extending beyond the duct boundaries, i.e. the question is not about a cantilever like the one shown in publication [1]. Hence, the fundamental problem in the publications of de Paula et al. is indeed the fact that the pressure to be measured and existing in a photoacoustic detector cell is only applied to a small portion of the total area of the pellicle,
35 resulting in a considerably lower response. In addition, there is a leak from under the pellicle which is large with respect to the duct size, which further reduces the pellicle response. The publications [2] and [3] further describe an optical angular

measurement for measuring the movement of a pellicle. However, the shape of a pellicle set forth in the cited publications is in practice unfavourable for angular measuring. Consequently, the solution proposed in publications [2] and [3] is not sufficiently responsive for highly accurate measurements and high precision applications.

Furthermore, atomic force microscopy uses cantilever typed pellicles. High frequencies are thus required from the pellicles, and, therefore, pellicles used in atomic force microscopy are not suitable for a photoacoustic detector.

Another problem in photoacoustic detection is a disturbance thereof as a result of external sounds. Thus, if the intra-chamber sound, infiltrated from outside the measuring instrument, is more powerful than the intrinsic noise of a system, the improvement regarding the sensitivity (response) of a detector system does not improve the determination of a gas to be analyzed. A typical method for reducing disturbances created by external sounds is sound proofing. Proofing is capable of damping external sounds at a coefficient of 10000-100000.

Another prior known means of reducing disturbances caused by external sounds comprises the use of double detection for a partial reduction of interfering sounds. In prior known double detection systems, a measuring system is provided which is identical to the regular measuring system, said identical system being denied the access of light, and it only measures sound within the chamber. Then, according to the solutions of prior art systems, there is performed a direct amplification of the difference between the actual measuring signal and a reference signal given by the identical measuring system. However, a problem with double detection systems as described above is e.g. that these systems only function in a special situation over a narrow frequency band. The problem is due to a phase difference created between sensors in the measuring systems.

Consequently, it is an object of the photoacoustic detector, the sensor for the photoacoustic detector and the method in the optimization of a door used as a sensor for the photoacoustic detector, in accordance with the invention, to eliminate or at least alleviate the above-described prior art problems.

Another object of the photoacoustic detector, the sensor for the photoacoustic detector and the method in the optimization of a door used as a sensor for the

photoacoustic detector, in accordance with the invention, is to provide an accurate and highly sensitive photoacoustic detector.

5 A further object of the present invention is to provide a photoacoustic detector, wherein the effect of disturbance factors resulting from external sounds on a measuring result has been reduced.

10 A further object of the photoacoustic detector according to a highly preferred embodiment of the present invention is to provide a method for improving the sensitivity of the photoacoustic detector and a photoacoustic detector, in which the photoacoustic detector comprises a sensor formed of a door, the sensitivity of which is improved by lowering a resonance angular frequency of the door.

15 A further object of the photoacoustic detector according to a highly preferred embodiment of the present invention is to provide a method for determining an optimal size of a chamber of the photoacoustic detector.

20 A further object of the photoacoustic detector according to a highly preferred embodiment of the present invention is to provide a highly sensitive sensor used in the photoacoustic detector and a method for optimization of the sensor.

In order to fulfill the above objects, among other things, the photoacoustic detector, the sensor for the photoacoustic detector and the method in the optimization of a door used as a sensor for the photoacoustic detector, all according to the invention,
25 are principally characterized by what is set forth in the characterizing clauses of the independent claims.

Thus, in a typical photoacoustic detector of the present invention, the means for detecting pressure variations created in the first chamber by absorbed infrared
30 radiation and/or light comprise at least an aperture provided in the wall of the first chamber, in association with which is provided a door adapted to be movable in response to the movement of a gas, and means for a contactless measurement of the door movement. In this context, the term contactless measurement is used in reference to measuring actions performed without one or more sensor that is
35 attached to a door, or in a mechanical communication or contact to it, such as, for example, without a piezoelectric sensor that is attached to a surface of a door. That is, in contactless measurement, measuring means that disturb and/or suppress the movement of a door, are not attached or connected to a door. Such contactless

measuring methods are, for example, different kinds of optical measuring methods. Furthermore, the above mentioned capacity measurement, in which the door of the present invention is arranged as the second sheet, is regarded as a contactless measuring method.

5

In a preferred photoacoustic detector according to the present invention, the door has a surface area which is at most equal to that of the aperture provided in the first chamber. In this context, the surface area of the aperture refers to a surface area of an imaginary level. The surface area of the door refers to a surface area of an azimuthal projection for a door that is projected in the imaginary level of the aperture. Thus, if the surface of the door is curved, for example, the real surface area of the door can be greater than that of the aperture, but the surface area of the azimuthal projection for a door according to the present invention is also then smaller than the surface area of the aperture.

15

In a preferred photoacoustic detector according to the present invention, the door is at least by one side mounted on a frame structure encircling the side faces of the door. Very advantageously, the door and the frame are fabricated from silicon, for example by forming a gap in a silicon wafer, the gap separating, excluding attachment points, the door from the rest of the wafer forming the frame.

20

In a preferred photoacoustic detector according to the present invention, the means for the contactless measurement of the door movement comprise: an optical measuring system, comprising at least one or more light sources for illuminating the door or a part thereof and one or more detectors for receiving light reflected from the door and for measuring the door movement as optical angular and/or translatory measurement, or a capacitive measuring system, whereby the door or a part thereof is coated with metal or the door is fabricated from an electrically highly conductive material, and which measuring system comprises a metal film or a metal-coated diaphragm set in the proximity of the door, as well as means for measuring the capacitance variations of a capacitor established by the door and the metal film. In some applications the system may comprise both optical and capacitive measuring systems. It is also possible that in addition to the optical and/or the capacitive measuring systems the photoacoustic detector comprises also other measuring systems for contactless measurement for the door movement.

25

30

35

In a highly preferred photoacoustic detector according to the present invention the means for the contactless measurement of the door movement are arranged in a

second chamber, which constitutes a measuring space with a volume V and which is in communication with the first chamber by way of the aperture of the first chamber aperture.

5 In a highly preferred photoacoustic detector according to the present invention, in communication with the second chamber is further provided a third chamber which is identical to the first chamber in terms of its size and has an aperture which is identical to that included in the first chamber and connects the third chamber with the second chamber, which aperture of the third chamber is closed with a door
10 similar to that closing the aperture of the first chamber, the movement of which door is measured in a manner similar to that used for measuring the movement of the door closing the first chamber aperture. Hence, the actual measuring signal and the reference signal can be measured separately and calculated for their amplitudes, the difference therebetween enabling an accurate filtration of external noises.

15 A typical sensor of a photoacoustic detector according to the present invention comprises a panel-like skirt element serving as a door frame, and a door separated from the panel-like skirt element by means of a gap. Preferably, the sensor is arrangible in communication with a chamber included in a photoacoustic detector
20 and containing a gas to be analyzed, such that the door is moved by pressure variations created in the chamber by absorbed infrared radiation and/or light.

The sensor according to a highly preferred embodiment of the present invention does not comprise sensors fixedly mounted thereon and/or fixedly arranged in
25 communication therewith for detecting and/or measuring the door movement.

The most important advantage of the present invention is its accuracy and sensitivity compared with typical photoacoustic detectors.

30 Furthermore, an advantage of the photoacoustic detector and the sensor of the photoacoustic detector according to the present invention is their simple structure and small size.

35 The most important advantage of the method in the optimization of a door used as a sensor for the photoacoustic detector according to the present invention is that the method is accurate and easy to apply in the optimization of the photoacoustic detector, and, especially in the optimization of the door used in it.

The invention will now be described in more detail with reference to the accompanying drawing, in which

- Fig. 1 shows schematically a design for a photoacoustic detector of the invention,
- Fig. 2 shows schematically a pressure sensor for a photoacoustic detector of the invention obliquely from above,
- Fig. 3a shows schematically a pressure sensor for a photoacoustic detector of the invention from the front,
- Fig. 3b shows schematically a pressure sensor for a photoacoustic detector of the invention in a cross-section,
- Fig. 4a shows schematically the effect of a resonance angular frequency ω_0 on an amplitude $A_x(\omega)$,
- Fig. 4b shows schematically modeling of a door resonance,
- Fig. 5 shows schematically a measuring system of the present invention for the movement of a pressure sensor door on the basis of angular variation of the door,
- Fig. 6 shows schematically a light intensity for a double detector in the measuring system of figure 5,
- Fig. 7 shows schematically a measuring system of the present invention for the movement of a pressure sensor door on the basis of a translatory measurement of the door,
- Fig. 8 shows schematically a measuring system of the present invention for the movement of a pressure sensor door, based on the use of a Michelson interferometer,
- Fig. 9 shows schematically an interference fringe developed on a triple detector in the measuring system of figure 8,
- Fig. 10 shows schematically discontinuities in a tangent,
- Fig. 11 shows schematically one preferred door design for a photoacoustic detector of the present invention,
- Figs. 12a and 12b show schematically a few optional door designs for a photoacoustic detector of the present invention, and
- Fig. 13 shows schematically a measuring system of the present invention for the movement of a pressure sensor door, by means of an optical multiplier based on multiple reflection.

Figure 1 shows schematically one embodiment for a photoacoustic detector of the present invention. As depicted in the figure, the photoacoustic detector comprises

gas-filled chambers V and V_0 , which contain or which can be supplied with a gas to be analyzed at a partial pressure p_x and a carrier gas at a partial pressure p_N (typically often nitrogen). The first chamber V_0 is composed of an annular housing element 1, having its first open end provided with a window 2 closing the first end of the chamber, through which infrared radiation or light in general can be guided into the chamber. The window 2 is preferably made highly transparent to infrared radiation and/or light and has preferably a thickness of about 3-6 mm. The chamber V_0 will be subsequently described in more detail regarding its dimensions and optimization thereof. The chamber V_0 has its second open end provided with a silicon door 3 closing the second end of the chamber at least partially, functioning as a pressure sensor, and having its design more closely depicted in figures 2 and 3. In some special applications, the silicon door 3 can also be replaced with a microphone, a thin Mylar or metal film. Arranged as an extension to the second end of the first chamber V_0 , the photoacoustic detector comprises a second chamber V , constituting a measuring space with a volume V . The measuring space is provided with measuring instruments for the silicon door movement. As shown in fig. 1, the measuring space has its second end closed with a reference system, comprising a reference chamber V_0 which is closed at one end and identical to the first chamber V_0 in size. The reference chamber has its first end closed with a silicon door similar to that used for the first chamber.

Figures 2, 3a and 3b depict schematically and by way of example one preferred silicon-made door according to the present invention, functioning as a pressure sensor. The pressure sensor comprises a panel-like skirt member serving as a door frame, and a door separated by a slit from the panel-like member. L is a width of the door, h its height, d its thickness, and Δ a width of the slot.

With low IR outputs of a light source conductible through the window into the chamber in a state of equilibrium, when $W(t) = W_{av} + W_0 \cos(2\pi ft)$, there follows

$$\left(\frac{dT}{dt} \right)_{T_0} = \frac{a_x p_x 2l (\cos \alpha)^{-1} W_0 \cos(2\pi ft)}{\sum_i c_V^i m_i} = \frac{a_x p_x 2l (\cos \alpha)^{-1} W_0 \cos(2\pi ft)}{V_0 \sum_i c_V^i \rho_i}, \quad (1)$$

where a_x is an absorption coefficient for a gas at a partial pressure p_x , l is a length of the chamber, α is an angle between the IR beam and the centre axis of the chamber, and $W(t)$ is a net light power proceeding into the chamber. That is, $W(t)$ is the light intensity $\times \pi R^2$, wherein R is a radius of the chamber, m_i is a mass of the

gas component, c_v^i is a specific heat capacity of the corresponding gas, ρ_i is a density of the gas i , and V_0 is a volume of the smaller chamber. For example

$$\sum_i c_v^i m_i = c_v^x m_x + c_v^N m_N = V_0 (c_v^x \rho_x + c_v^N \rho_N).$$

5

It is a default in equation (1) that $\tau \ll f^{-1} \ll \tau_0$, wherein τ_0 is a time constant for heat conduction out of the chamber and τ is a time constant for the conversion of absorption energy to heat.

Further

10

$$\Delta T = T(t) - T_0 = \int_{T_0} \left(\frac{dT}{dt} \right) dt = \frac{a_x p_x 2l (\cos \alpha)^{-1} W_0 \sin(2\pi f t)}{2\pi f V_0 \sum_i c_v^i \rho_i}. \quad (2)$$

An equation of state for the ideal gas results in

15

$$\frac{dp}{p_0} + \frac{dV}{V_0} = \frac{dT}{T_0}. \quad (3)$$

In the pressure sensor:

$$\begin{aligned} dV &\approx \frac{1}{2} x A \\ A dp &= kx = F, \end{aligned} \quad (4)$$

20

where A represents a surface area of the pressure sensor, k is a spring constant, and x is a motion. From equations (3) and (4) is obtained

$$x \approx \frac{\Delta T / T_0}{\frac{k}{A p_0} + \frac{A}{2 V_0}} \quad (\omega = 0). \quad (5)$$

25

Because ΔT presented in equation (2) is modulated by an angular frequency ω , it is necessary to examine an equation of motion for the door (or the diaphragm), i.e.

$$m \ddot{x} - \underbrace{2\beta m \dot{x}}_k + m \omega_0^2 x = F_0 e^{i \omega t} \quad (6)$$

30

where $F_0 e^{i\omega t}$ represents a periodic force, β is an damping constant, $\omega_0 = \sqrt{k/m}$ is a resonance angular frequency, and x is a motion either from the end of a door or from the middle of a door or a diaphragm. The solution for equation (6)

$$x = \frac{(F_0/m)e^{i\omega t}}{\omega_0^2 - \omega^2 + 2i\omega\beta}, \quad (7)$$

from which is obtained an amplitude

$$\sqrt{x * x} = A_x(\omega) = \frac{F_0/m}{\sqrt{(\omega_0^2 - \omega^2)^2 + 4\beta^2\omega^2}}. \quad (8)$$

Equations (3) and (4) provide for amplitudes

$$\frac{\Delta p}{p_0} = \frac{\Delta T}{T_0} - \frac{\Delta V}{V_0} = \frac{\Delta T}{T_0} - \frac{1}{2} A_x(\omega) \frac{A}{V_0}$$

and hence

$$A_x(\omega) = \frac{A\Delta p/m}{\sqrt{(\omega_0^2 - \omega^2)^2 + 4\beta^2\omega^2}} = \frac{Ap_0 \left(\frac{\Delta T}{T_0} - \frac{A_x(\omega)A}{2V_0} \right)}{m\sqrt{(\omega_0^2 - \omega^2)^2 + 4\beta^2\omega^2}},$$

from which

$$A_x(\omega) = \frac{Ap_0 \frac{\Delta T}{T_0}}{m\sqrt{(\omega_0^2 - \omega^2)^2 + 4\beta^2\omega^2} + \frac{p_0 A^2}{2V_0}} \quad (9)$$

Figure 4a shows schematically the effect of a resonance angular frequency ω_0 on a door or diaphragm amplitude $A_x(\omega)$.

If $\omega = 0$, then equation (9) results in equation (5), i.e. $A_x(0) = x$, because $m\omega_0^2 = k$.

It is preferred that the resonance of a door or a diaphragm be modelled in such a way that the increase of amplitude brought by resonance around ω_0 is not taken into consideration (see fig. 4b). That is, if $\omega < \omega_0$, the result is

$$A_x(\omega) \approx \frac{Ap_0 \Delta T/T_0}{m\omega_0^2 + \frac{p_0 A^2}{2V_0}} = \frac{p_0 \Delta T/T_0}{\frac{m\omega_0^2}{A} + \frac{p_0 A}{2V_0}} = \frac{p_0 \Delta T/T_0}{\rho d \omega_0^2 + \frac{p_0 A}{2V_0}}, \quad (10)$$

and if $\omega > \omega_0$, the result is

$$A_x(\omega) \approx \frac{p_0 \Delta T/T_0}{\rho d \omega^2 + \frac{p_0 A}{2V_0}}, \quad (11)$$

10

where ρ represents a door (or diaphragm) density and d is a thickness. If resonance is not utilized, it is advisable to use a door (or a diaphragm) at less than the resonance angular frequency ω_0 , i.e. to use equation (10), which indicates that the optimization, i.e. maximization, of amplitude $A_x(\omega)$ for door (or a diaphragm) movement must be done by means of ω_0 , d , V_0 and A . The lower ω_0 and A are, the higher is $A_x(\omega)$.

15

Amplitude reaches a maximum, when $\rho d \omega_0^2 + \frac{p_0 A}{2V_0}$ reaches a minimum. This happens when

20

$$\rho d \omega_0^2 \approx \frac{p_0 A}{2V_0} \quad (12)$$

and

25

$$A_x^{opt}(\omega) \approx \frac{p_0 \Delta T/T_0}{2\rho d \omega_0^2} = \frac{p_0 \Delta T/T_0}{2 \frac{p_0 A}{2V_0}} \quad (13)$$

By means of equations (1) and (2), the result from equation (13) is

$$A_x^{opt}(\omega) \approx \frac{p_0 a_x p_x l (\cos \alpha)^{-1} W_0}{T_0 \omega V_0 \sum_i c_i \rho_i \rho d \omega_0^2}, \quad (14)$$

where $\omega \leq \omega_0$. The equation indicates that the best way to augment a response is to reduce angular frequencies ω and ω_0 . It is to be noted, that by disregarding or without optimizing the term $\frac{p_0 A}{2V_0}$, the best possible optimization result will not be

attained. Thus, optimization can and typically should be carried out by optimizing also factors A and/or d . With typical commercially available microphones, the resonance frequency $f_0 = \omega_0 / 2\pi$ is typically 10-20 kHz. If a microphone, whose resonance frequency $f_0 = 20$ kHz, is operated close to the resonance frequency, the result is A_x^{opt} (20 kHz). If a similar diaphragm is used to construct a new microphone, whose resonance frequency $f_0 = 500$ Hz, then

10

$$A_x^{opt}(500\text{Hz}) = \left(\frac{20\text{kHz}}{0,5\text{kHz}} \right)^3 A_x^{opt}(20\text{kHz}) = 40^3 A_x^{opt}(20\text{kHz}) = 64000 A_x^{opt}(20\text{kHz}), \quad (15)$$

provided that the microphones are optimized according to equation (12). Further, if a microphone optimized for the frequency of 500 Hz were operated at the frequency of 50 Hz, the response would further grow tenfold and the improvement factor would thus be 640000. The resonance frequency can be decreased on the basis of a subsequent equation (16) by making a door (or a diaphragm) thinner. This provides a further improvement at a ratio d_1/d_2 provided that the thinning of a door or a diaphragm is technically possible.

20

Resonance angular frequencies depend on the dimensions and material of a door (or a diaphragm). For a door

$$\omega_0 = \sqrt{\frac{2E}{3\rho}} \frac{d}{L^2}, \quad A = Lh, \quad (16)$$

25

where E is a Young's modulus for the material, ρ is a density, L is a width of the door, h is a height, and d is a thickness.

For a circular metal diaphragm, which is not under tension

30

$${}_E \omega_0 = \sqrt{\frac{E}{3\rho(1-\sigma^2)}} \frac{4d}{r^2}, \quad (17)$$

where σ = Poisson's ratio and r is a radius of the diaphragm.

For a tensioned thin film (for example Mylar)

$$\omega_0 = \frac{2.4\sqrt{T/\mu}}{r} = \frac{2.4}{r} \sqrt{\frac{F}{2\pi\rho d}}, \quad (18)$$

5

where T represents a tension of the film and μ is a mass/unit area, i.e. $\mu = m/a = \rho dA/A = \rho d$.

To be exact, even for a thin film (Mylar 2 μm) applies

$$\omega_{\text{tot}}^2 = \omega_E^2 + \omega_T^2, \quad (19)$$

where nevertheless $\omega_E^2 \ll \omega_T^2$.

15 If comparison is made between a door according to one exemplary embodiment of the present invention, fabricated from the same material (silicon) and having a height L/s , with a circular diaphragm not under tension, the result will be

$$\frac{A_{\text{door}}^{\text{opt}}}{A_{\text{film}}^{\text{opt}}} \approx s\pi \left[\frac{8}{s\pi(1-\sigma^2)} \right]^{1/2} \approx 20, \quad (20)$$

20 if $s = 10$, i.e. the door has a height which is one tenth of the width L .

If comparison is made between a door according to one exemplary embodiment of the present invention with a tensioned Mylar film usually employed in prior art microphones, the result will be

25

$$\frac{A_{\text{door}}^{\text{opt}}}{A_{\text{Mylar}}^{\text{opt}}} \approx 43 \left(\frac{F}{N} \right)^{1/2}, \quad (21)$$

where F represents a total tensile force in Newtons and $s = 10$. The ratio is typically 10-20, depending on how little force F is required to make the film functional.

30

Thus, a door according to the present invention provides a solution which imparts an improvement of at least one order of magnitude in the response of a sensor. If this improvement is added to that gained by angular frequency, a low resonance door

can be created which provides in a highly advantageous manner an improvement of a few million in the response of a sensor.

5 The use of a door-sensor according to one embodiment of the present invention requires that a slot or gap between the door and the wall be preferably made as narrow as possible. The chamber leaks through the gap, with the result that the sensor has a lower limiting frequency f_{cut} , which is defined by a door gap area a as follows:

$$10 \quad f_{cut} \propto v_0 \frac{a}{V_0}, \quad (22)$$

where v_0 is a velocity of sound in the chamber and $V \gg V_0$.

15 On the other hand, it is beneficial to have a small hole between the chambers for equalizing slow pressure variations between the chambers, and which hole can thus be designed as the above-mentioned gap between the door and the door frame.

20 The accuracy of a photoacoustic sensor can be improved also by replacing the prior art capacitive measuring of a door (or diaphragm) movement with an optical measuring system of the present invention. Optical measuring causes very little interference with the movement of a door (or a diaphragm). According to the present invention, the movement can be measured either by means of an angle assumed by a door (or a diaphragm) or by means of a translatory movement of some point in a door (or a diaphragm).

25 Figure 5 illustrates a measuring system based on angular measurement, wherein an optical indicator in the form of a laser 10 is used, while the detector is a double sensor 11. Besides a door 3, which serves as a sensor, the measuring system comprises the laser 10 as a light source, an optical lens 12 for focusing a light beam, and the double sensor 11 for receiving and measuring a light beam v reflected from the door 3. Hence, the double sensor comprises a first detector d1 and a second detector d2. The light beam v has its focus 13 at the double sensor. Figure 6 depicts a light power of the measuring system on a double sensor, wherein at each point of y the intensity of light is integrated in a direction perpendicular to y .

35 In the angular measurement shown in figures 5 and 6, an angle variation $\Delta\alpha$ is converted to a translatory motion $\Delta y = a2\Delta\alpha$, which is measured with a double

sensor d_1, d_2 . The angle $\Delta\alpha$ represents an average angle variation in the door area illuminated by a laser beam. Generally, $\Delta\alpha$ depends on a measuring spot, i.e. l .

$$\tan \Delta\alpha = \frac{FL^2}{6EI} \left[1 - \left(\frac{L-l}{L} \right)^3 \right] = \frac{8EI\Delta x L^2}{6L^3 EI} \left[1 - \left(\frac{L-l}{L} \right)^3 \right] = \frac{4\Delta x}{3L} \left[1 - \left(\frac{L-l}{L} \right)^3 \right], \quad (27)$$

or

$$\Delta y \approx 2a \frac{4\Delta x}{3L} \left[1 - \left(\frac{L-l}{L} \right)^3 \right]. \quad (28)$$

The smallest movement that can be measured with a double sensor is

$$\Delta y_{\min} = \frac{\sigma}{2(S/N)}, \quad (29)$$

where σ is the half width of a laser focus. At its minimum, σ is limited by diffraction, i.e.

$$\sigma \approx \frac{\lambda}{D}(a+b). \quad (30)$$

Thus, the detectable minimum movement at the end of a door is

$$\Delta x_{\min} \approx \frac{3L\Delta y_{\min}}{8a \left[1 - \left(\frac{L-l}{L} \right)^3 \right]} = \frac{3L\lambda(a+b)}{2D(S/N)8a \left[1 - \left(\frac{L-l}{L} \right)^3 \right]} = \frac{3L\lambda(a+b)}{16aD \left[1 - \left(\frac{L-l}{L} \right)^3 \right] (S/N)}. \quad (31)$$

The illuminated area at the door has a width $aD/[(a+b)\cos\beta]$, which provides a final limitation. If $b \approx 0$ and $l \approx L$, the preceding equation results in

$$\Delta x_{\min} \approx \frac{3L\lambda}{16D(S/N)}. \quad (32)$$

In practice $D \leq L$, i.e.

$$\Delta x_{\min} \approx \frac{3\lambda}{16(S/N)}, \quad (33)$$

where S is a laser intensity I_0 and N is a sum noise of light and electronics.

The amplitude of a signal (fluctuation of light power)

$$A_v = \Delta P_{d_1} - \Delta P_{d_2} = 2\Delta y I_{\max}, \quad (34)$$

where ΔP_{d_1} and ΔP_{d_2} represent changes of light power at detectors d_1 and d_2 , as well as I_{\max} is a maximum light power / Δy . Now, with the help of equation (28)

5

$$A_v = a \frac{16A_x I_{\max}}{3L} \left[1 - \left(\frac{L-l}{L} \right)^3 \right] \approx \frac{16aA_x}{3L} \frac{P_{d_1} + P_{d_2}}{\sigma} \left[1 - \left(\frac{L-l}{L} \right)^3 \right], \quad (35)$$

where $P_{d_1} + P_{d_2} = I_0$ represent the light power of a laser falling on the double sensor.

Thus, the optical indicator has a light signal whose amplitude is

10

$$A_v = \frac{16aDI_0A_x}{3L\lambda(a+b)} \approx \frac{16I_0A_x}{3\lambda}, \quad (36)$$

where A_x is the amplitude of door movement x , which must be $< \lambda$.

- 15 One of the benefits offered by an optical indicator of the present invention is its simple design, it does not interfere with door movement, and the double sensor suppresses the photon noise of laser light. Preferably, the size of a laser light spot on the door is large, $D \approx L$, in order to have a small σ . The optical indicator of the present invention can also be used for measuring a diaphragm movement, the
20 optimal measuring site being $r/\sqrt{3}$.

- Thus, according to the present invention, the door movement can also be measured in a translatory measurement. Figure 7 depicts a measuring system of the present
25 invention, which is not an angular measurement and by which a translatory movement x of the door can be measured. In addition to the door, the measuring system comprises a laser 10 serving as a light source, a double sensor 11, a first optical 12 lens for directing a light beam focus to the surface of a door 3 presently at rest or in stationary condition, and a second optical lens 12 for focusing on the
30 double detector a light beam reflected from the door 3. The light source, the optical lenses and the double detector are arranged in such a way that, when the door is at rest, the angle between light beams incident on and reflecting from the door is 90 degrees. An advantage of the measurement is among other things that the laser beam is in focus at the door surface and the door may have a poor optical quality. The
35 minimum movement that can be detected by the measuring system is

$$\Delta x_{\min} \approx \frac{\sqrt{2}a\lambda}{4D(S/N)}, \quad (37)$$

if the door has a mirror surface.

5

The minimum movement is in the same order of magnitude as in angular measurement, i.e. $\Delta x_{\min} = \lambda/(S/N)$, if $D = \sqrt{2}a/4$. Translatory measurement is also suitable for measuring a diaphragm movement, as well.

- 10 According to one preferred embodiment of the invention, the movement of a door (or a diaphragm) can also be measured optically by using an interferometer. Figure 8 illustrates one measuring system of the present invention for measuring the movement of a door (or a diaphragm) by means of a so-called Michelson interferometer. As shown in the figure, the system comprises, in addition to the door
- 15 itself, a laser 10 serving as a light source, an optical lens 12 for focusing a laser beam, a beam splitter 15 or a semi-transparent mirror for splitting the laser beam for the door and for a reference mirror 16, the reference mirror 16 and a triple sensor 17 for receiving the laser beams coming from the beam splitter 15. According to what is shown in the figure, the laser beam is approximately in focus both at the door and
- 20 at the reference mirror. The reference mirror 16 is adjusted such that the triple detector 17, constituted by three sensors d1, d2 and d3, develops $3/4$ of the interference fringe perpendicular to the plane of paper. When x changes as the door is moving, the interference fringe moves laterally across the detectors, as shown in figure 9. The fringe moves across a single fringe gap, when x changes by $\lambda/2$. The
- 25 intensity distribution of the fringe is

$$I(z) = \frac{1}{2}A \left[1 + \cos \left(2\pi \frac{z}{D} \right) \right]. \quad (38)$$

- If the interference fringe moves by ε , signals I_1 , I_2 and I_3 of the sensors d_1 , d_2 and d_3
- 30 are obtained as follows:

$$I_1(\varepsilon) = \int_{\frac{2D}{4} + \varepsilon}^{\frac{D}{4} + \varepsilon} \frac{A}{2} \left[1 + \cos \left(2\pi \frac{z}{D} \right) \right] dz = \frac{AD}{2 \cdot 4} + \frac{AD}{2 \cdot 2\pi} \left[-\cos \left(2\pi \frac{\varepsilon}{D} \right) + \sin \left(2\pi \frac{\varepsilon}{D} \right) \right], \quad (39)$$

$$I_2(\varepsilon) = \int_{\frac{D}{4} + \varepsilon}^{\varepsilon} \frac{A}{2} \left[1 + \cos\left(2\pi \frac{z}{D}\right) \right] dz = \frac{AD}{2 \cdot 4} + \frac{AD}{2 \cdot 2\pi} \left[\cos\left(2\pi \frac{\varepsilon}{D}\right) + \sin\left(2\pi \frac{\varepsilon}{D}\right) \right] \text{ and (40)}$$

$$I_3(\varepsilon) = \int_{\varepsilon}^{\frac{D}{4} + \varepsilon} \frac{A}{2} \left[1 + \cos\left(2\pi \frac{z}{D}\right) \right] dz = \frac{AD}{2 \cdot 4} + \frac{AD}{2 \cdot 2\pi} \left[\cos\left(2\pi \frac{\varepsilon}{D}\right) - \sin\left(2\pi \frac{\varepsilon}{D}\right) \right]. \quad (41)$$

5 Thus,

$$\begin{cases} I_2(\varepsilon) - I_1(\varepsilon) = \frac{AD}{2\pi} \cos\left(2\pi \frac{\varepsilon}{D}\right) \\ I_2(\varepsilon) - I_3(\varepsilon) = \frac{AD}{2\pi} \sin\left(2\pi \frac{\varepsilon}{D}\right) \end{cases} \quad (42)$$

or

10

$$\frac{2\pi\varepsilon}{D} = \tan^{-1} \left\{ \frac{I_2 - I_3}{I_2 - I_1} \right\}. \quad (43)$$

Because $\varepsilon = \Delta z = 2D\Delta x / \lambda$, then

15

$$\Delta x = \frac{\lambda}{4\pi} \tan^{-1} \left\{ \frac{I_2 - I_3}{I_2 - I_1} \right\} \quad (44)$$

Since the signals $I_2 - I_1$ and $I_2 - I_3$ are in a 90° phase relative to each other, they can provide a way across tangent function discontinuities shown in figure 10. Hence, in equation

20

$$\Delta x = \left(k + \frac{1}{2} \right) \frac{\lambda}{4} + \frac{\lambda}{4\pi} \tan^{-1} \left\{ \frac{I_2 - I_3}{I_2 - I_1} \right\}$$

it is possible to measure changes ± 1 of an integer k at tangent discontinuities $\phi = (n + \frac{1}{2})\pi$.

25

The smallest detectable movement is

$$\Delta x_{\min} = \frac{\sigma}{2(S/N)} = \frac{\lambda}{8(S/N)}, \quad (45)$$

where $S=I_0/2$.

- 5 If the door movement is small $<\lambda/4$, the triple sensor of the above-described measuring system can be replaced by a double sensor the same way as in the optical indicator. Thus, the combined width of the sensors is equal to the width of a single fringe and

$$\begin{cases} I_1 + I_2 = \frac{AD}{2} = \frac{I_0}{2} \\ I_1 - I_2 = \frac{AD}{\pi} \sin\left(2\pi \frac{\varepsilon}{D}\right) \end{cases} \quad (46)$$

Because $\varepsilon = \Delta z = 2D\Delta x/\lambda$ is

$$\Delta x = \frac{\lambda}{4\pi} \sin^{-1} \left\{ \frac{I_1 - I_2}{I_1 + I_2} \right\} \approx \frac{\lambda}{8} \frac{I_1 - I_2}{I_1 + I_2} = \frac{\lambda}{4I_0} (I_1 - I_2), \quad (47)$$

15

where I_0 is the laser light power. Then, the amplitude of the light signal is

$$A_I = I_1 - I_2 \approx 4 \frac{I_0 A_x}{\lambda}, \quad (48)$$

- 20 where A_x is the amplitude of the door movement x .

Advantages gained by interferometric measurement according to the present invention include, among other things: According to equation (44), the response is highly linear even when the movement of a door (or a diaphragm) covers several
25 wavelengths. Absolute accuracy is high, because the shape of an interference signal is precisely consistent with $1/2(1+\cos(2\pi z/D))$. In addition, a laser can be focused on the measuring point of a door in an almost dot-like manner and the result is not affected by diffraction. Neither is the value of a measuring result affected by fluctuation of the laser intensity I_0 , since the value of the maximum intensity A is
30 reduced away in equation (44).

When comparing the optical indicator and the interferometer with each other, it can be concluded that the equation (33) does not work out in practice, because a square (rectangular) door is not the optimal form when optimizing the equation (10). That is, in other words, the optical indicator and the interferometer of the present invention function very well also with a square (rectangular) door, but should a further improvement in sensitivity and accuracy be desired, the door shape must be changed. When using a door whose height is one tenth of its width L (i.e. $s = 10$), according to fig. 11 the equation (31) results in

$$\Delta x_{\min} \approx \frac{3L\lambda}{16L/10(S/N)} \approx \frac{2\lambda}{S/N}, \quad (49)$$

which is 16-fold with respect to the corresponding value of an interferometer (equation (45)). Further, the interferometer will be improved with respect to the optical indicator, if s grows, i.e. the door becomes shorter, which, on the other hand, also increases the amplitude $A_x(\omega)$ of door movement.

The configuration of a door can still be improved, for example by further reducing a resonance frequency by weakening a door hinge by grooving the hinge in its mid-section as shown in figure 12a and/or by augmenting the surface area of a door at the end of the door as shown in figure 12b. The door design shown in figure 12b is particularly suitable for the multiplier solution of an interferometer as described in more detail hereinafter. The door shown in figure 12b can be realized also by using more than one bar, whereby stiffness of the door increases and rotation of the door resulting in the pressure on the door diminishes. According to the present invention, the door can be realized also in such a manner, that the door, the surface area of which is smaller than the surface of the aperture, is hinged by using a long bar, whereby the structure shown in figure 12a, for example, can act as a bar, the door being attached to a head of the bar or formed as part of an end of the bar. An advantage of a long bar is that the use of a long bar reduces door resonance.

Since the use of an interferometer develops an almost dot-like spot on the door, it is possible to apply multiple reflection, i.e. a multiplier, in the interferometer as shown in figure 13. Laser light v travels to an end mirror, reflecting n times from the door 3 and from a fixed plane mirror 20, which is mounted in the vicinity of the door and preferably arranged parallel to the door surface. The laser has its focus in the proximity of the end mirror 21, from which the laser beam returns along the same path, reflecting another n times from the door. If the door nudges a distance Δx , the

optical distance changes in the interferometer by $4n\Delta x$ and the response increases $2n$ fold, if there are no reflection losses.

If the mirrors and the door have a reflection coefficient R , the equation (45) adopts
5 now a new form:

$${}_R x_{\min} = \frac{\lambda}{2nR^{4n-2}8(S/N)} = \frac{x_{\min}}{2nR^{4n-2}}. \quad (50)$$

This method provides about a 10-fold augmentation of sensitivity. Multiple
10 reflection can also be applied in a laser reflection of the present invention for translatory measurement, since the laser has its focus on the door.

When comparing an optical indicator of the present invention and an interferometer
with each other, it can be concluded that both measuring systems of the present
15 invention are capable of providing a substantial improvement regarding the accuracy and sensitivity of measurement. Interferometric measurement is even somewhat more precise than an optical indicator, but at the same time the measuring system is slightly more complicated. Hence, the required sensitivity should be considered in light of a specific application and case for selecting the appropriate measuring
20 method.

As stated above, a problem with prior known photodetectors is disturbance caused by external sounds. According to the present invention, the effect of external sounds can be suppressed by means of a per se known double detector, which is shown in
25 fig. 1. According to the present invention, the actual measuring signal and a reference signal are measured separately and calculated for their amplitudes, the difference therebetween enabling a more accurate and effective filtration of external noises. Especially in a frequency range, where there is no signal developed by a gas, the interfering noise can be substantially reduced.

30 There is no intention whatsoever to limit the invention to the embodiment described in the foregoing disclosure, but it can be varied within the scope of the inventive concept set forth in the claims.

35

Literature references:

5

[1] Nicolas Ledermann et. al., Integrated Ferroelectrics, Vol. 35, pp. 177-184 (2001)

[2] M.H. de Paula et. al., J. Appl. Phys., Vol. 64, 3722-3724 (1988)

[3] M.H. de Paula et. al., Rev. Sci. Instrum., Vol. 673, 3487-3491 (1992)

Claims:

1. A photoacoustic detector, comprising at least
 - a first chamber (V_0) suppliable with a gas to be analyzed,
- 5 - a window for letting modulated and/or pulsed infrared radiation and/or light in the first chamber (V_0), and
 - means for detecting pressure variations created in the first chamber by absorbed infrared radiation and/or light, **characterized** in that the means for detecting pressure variations created in the first chamber by absorbed infrared radiation and/or
- 10 light comprise at least
 - an aperture provided in the wall of the first chamber (V_0), in communication with which is provided a door adapted to be movable in response to the movement of a gas, and
 - means for a contactless measurement of the door movement.
- 15 2. A photoacoustic detector as set forth in claim 1, **characterized** in that the door has a surface area which is at most equal to that of the aperture provided in the first chamber (V_0).
- 20 3. A photoacoustic detector as set forth in claim 1 or 2, **characterized** in that the door is at least by one side mounted on a frame structure encircling the side faces of the door.
- 25 4. A photoacoustic detector as set forth in any of the preceding claims, **characterized** in that the door and the frame are fabricated from silicon.
5. A photoacoustic detector as set forth in any of the preceding claims, **characterized** in that the means for a contactless measurement of the door movement comprise:
 - 30 - an optical measuring system, comprising at least one or more light sources for illuminating the door or a part thereof and one or more detectors for receiving light reflected from the door and for measuring the door movement as optical angular and/or translatory measurement, or
 - 35 - a capacitive measuring system, whereby the door or a part thereof is coated with a metal or the door is fabricated from an electrically highly conductive material, and said measuring system comprising a metal film or a metal-coated diaphragm set in the proximity of the door, as well as means for measuring the capacitance variations of a capacitor established by the door and the metal film.

6. A photoacoustic detector as set forth in claim 5, **characterized** in that the light source of the measuring system comprises a laser.

5 7. A photoacoustic detector as set forth in claim 5 or 6, **characterized** in that the detector of the measuring system comprises a double sensor.

8. A photoacoustic detector as set forth in any of claims 5-7, **characterized** in that the light source and the detector are designed as a part of an interferometer.

10

9. A photoacoustic detector as set forth in any of claims 5-8, **characterized** in that the means of a contactless measurement of the door movement are provided in a second chamber (V), which constitutes a measuring space with a volume V and which is in communication with the first chamber by way of the first chamber's aperture.

15

10. A photoacoustic detector as set forth in claim 9, **characterized** in that in communication with the second chamber is further provided a third chamber which is identical to the first chamber in terms of size and has an aperture which is identical to that included in the first chamber and connects the third chamber with the second chamber, said aperture of the third chamber being closed with a door similar to that closing the aperture of the first chamber, the movement of said door being measured in a manner similar to that used for measuring the movement of the door closing the first chamber aperture, as well as means for calculating the amplitudes of an actual measuring signal measured from the sensor arranged in the first chamber aperture and a reference signal measured from the sensor arranged in the third chamber aperture, and for working out a difference therebetween.

20

25

11. A sensor for a photoacoustic detector, **characterized** in that the sensor comprises a panel-like skirt element serving as a door frame, and a door separated from the panel-like skirt element by means of a gap.

30

12. A sensor as set forth in claim 11, **characterized** in that the sensor is arrangeable in communication with a chamber included in a photoacoustic detector and containing a gas to be analyzed, such that the door is moved by pressure variations created in the chamber by absorbed infrared radiation and/or light.

35

13. A sensor as set forth in claim 11 or 12, **characterized** in that the sensor does not comprise sensors fixedly mounted thereon and/or fixedly arranged in communication therewith for detecting and/or measuring the door movement.

- 5 14. A method in the optimization of a door used as a sensor for a photoacoustic detector, **characterized** in that the optimization of the amplitude of a door movement is implemented by applying the optimization equation:

$$\begin{aligned}
 &A_x(\omega) \approx \frac{p_0 \Delta T / T_0}{\rho d \omega_0^2 + \frac{p_0 A}{2V_0}}, & \text{when } \omega < \omega_0 \\
 10 \quad &A_x(\omega) \approx \frac{p_0 \Delta T / T_0}{\rho d \omega^2 + \frac{p_0 A}{2V_0}}, & \text{when } \omega > \omega_0
 \end{aligned}$$

15. A method as set forth in claim 14, **characterized** in that optimization of the amplitude $A_x(\omega)$ is effected by means of ω_0 , A and d , especially by striving to reduce the values thereof.




FIG. 1




FIG. 2




FIG. 3a




FIG. 3b

2/6




FIG. 4a




FIG. 4b




FIG. 7




FIG. 8

5/6




FIG. 9




FIG. 10

6/6




FIG. 11




FIG. 12a

FIG. 12b




FIG. 13

INTERNATIONAL SEARCH REPORT

International application No.

PCT/FI 2003/000684

A. CLASSIFICATION OF SUBJECT MATTER

IPC7: G01N 21/37, G01J 5/42

According to International Patent Classification (IPC) or to both national classification and IPC

B. FIELDS SEARCHED

Minimum documentation searched (classification system followed by classification symbols)

IPC7: G01N

Documentation searched other than minimum documentation to the extent that such documents are included in the fields searched

SE,DK,FI,NO classes as above

Electronic data base consulted during the international search (name of data base and, where practicable, search terms used)

C. DOCUMENTS CONSIDERED TO BE RELEVANT

Category*	Citation of document, with indication, where appropriate, of the relevant passages	Relevant to claim No.
X	EP 0389071 A2 (DRESSER INDUSTRIES INC), 26 Sept 1990 (26.09.1990), page 3, line 21 - line 24; page 3, line 29 - line 33; page 5, line 41 - page 6, line 3, page 6, line 20 - line 24, figure 1	1-5
A	---	11-13
X	US 6222190 B1 (BERNSTEIN, R. ET AL), 24 April 2001 (24.04.2001), column 1, line 66 - column 2, line 10, figure 1, abstract	11-13
A	---	1-5

☒ Further documents are listed in the continuation of Box C.☒ See patent family annex.

* Special categories of cited documents:

- "A" document defining the general state of the art which is not considered to be of particular relevance
- "E" earlier application or patent but published on or after the international filing date
- "L" document which may throw doubts on priority claim(s) or which is cited to establish the publication date of another citation or other special reason (as specified)
- "O" document referring to an oral disclosure, use, exhibition or other means
- "P" document published prior to the international filing date but later than the priority date claimed

"T" later document published after the international filing date or priority date and not in conflict with the application but cited to understand the principle or theory underlying the invention

"X" document of particular relevance: the claimed invention cannot be considered novel or cannot be considered to involve an inventive step when the document is taken alone

"Y" document of particular relevance: the claimed invention cannot be considered to involve an inventive step when the document is combined with one or more other such documents, such combination being obvious to a person skilled in the art

"&" document member of the same patent family

Date of the actual completion of the international search

23 February 2004

Date of mailing of the international search report

2.7 -02- 2004

Name and mailing address of the ISA/

Swedish Patent Office
Box 5055, S-102 42 STOCKHOLM
Facsimile No. +46 8 666 02 86

Authorized officer

Anna Lundqvist /ITW
Telephone No. +46 8 782 25 00

INTERNATIONAL SEARCH REPORT

International application No.

PCT/FI 2003/000684

C (Continuation). DOCUMENTS CONSIDERED TO BE RELEVANT

Category*	Citation of document, with indication, where appropriate, of the relevant passages	Relevant to claim No.
P,X	US 6474168 B1 (MERINGDAL, F.), 5 November 2002 (05.11.2002), column 1, line 24 - line 30; column 3, line 51 - line 65; column 5, line 13 - line 43	11-13
P,A	--	1-5
A	US 4557603 A (OEHLER, O. ET AL), 10 December 1985 (10.12.1985), column 2, line 64 - column 3, line 6; column 15, line 19 - line 29	1-5, 11-13
A	--	
A	US 6082178 A (BERNSTEIN, R. ET AL), 4 July 2000 (04.07.2000), column 1, line 36 - line 42, abstract	1-5, 11-13
A	--	
A	US 4355234 A (FERTIG, G.H. ET AL), 19 October 1982 (19.10.1982), column 2, line 37 - line 44	1-5, 11-13
	-- -----	

INTERNATIONAL SEARCH REPORT

International application No.
PCT/FI 2003/000684

Box No. II Observations where certain claims were found unsearchable (Continuation of item 2 of first sheet)

This international search report has not been established in respect of certain claims under Article 17(2)(a) for the following reasons:

1. ☐ Claims Nos.:
because they relate to subject matter not required to be searched by this Authority, namely:

2. ☐ Claims Nos.:
because they relate to parts of the international application that do not comply with the prescribed requirements to such an extent that no meaningful international search can be carried out, specifically:

3. ☐ Claims Nos.:
because they are dependent claims and are not drafted in accordance with the second and third sentences of Rule 6.4(a).

Box No. III Observations where unity of invention is lacking (Continuation of item 3 of first sheet)

This International Searching Authority found multiple inventions in this international application, as follows:

see extra sheet

1. ☐ As all required additional search fees were timely paid by the applicant, this international search report covers all searchable claims.
2. ☐ As all searchable claims could be searched without effort justifying an additional fee, this Authority did not invite payment of any additional fee.
3. ☐ As only some of the required additional search fees were timely paid by the applicant, this international search report covers only those claims for which fees were paid, specifically claims Nos.:

4. ☒ No required additional search fees were timely paid by the applicant. Consequently, this international search report is restricted to the invention first mentioned in the claims; it is covered by claims Nos.:
1-5, 11-13

Remark on Protest

- ☐ The additional search fees were accompanied by the applicant's protest.
☐ No protest accompanied the payment of additional search fees.

The present application relates to 4 different inventions. The separate inventions are:

Invention 1: Claims 1-4 and 11-13 relate to a photo acoustic detector including a first chamber with a window admitting infrared radiation/light to get through. The chamber wall has an aperture in communication with a membrane. The membrane is movable in response to the movement of the gas, which moves when it absorbs the infrared radiation/light.

Invention 2: Claims 5-10 relate to a photo acoustic detector including a first chamber with a window admitting infrared radiation/light to get through. The chamber wall has an aperture in communication with a membrane. The membrane is movable in response to the movement of the gas, which moves when it absorbs the infrared radiation/light. The detector includes light sources for illuminating the membrane and detectors for receiving the reflected light for optic measurement of the membrane movement.

Invention 3: An alternative solution in claim 5 also relates to a photo acoustic detector including a first chamber with a window admitting infrared radiation/light to get through. The chamber wall has an aperture in communication with a membrane. The membrane is movable in response to the movement of the gas, which moves when it absorbs the infrared radiation/light. The membrane is fabricated from an electrically highly conductive material or is coated with a metal. The measuring system includes a metal-coated diaphragm in the proximity of the membrane, composing a capacitor together with the membrane.

Invention 4: Claims 14-15 relate to a method for optimizing the amplitude of the membrane movement applying a certain optimization equation.

The special technical feature of invention 1 is to provide a contactless measurement of the membrane movement.

The special technical feature of invention 2 is to provide a contactless measurement of the membrane movement using optical angular and/or translatory measurements.

The special technical feature of invention 3 is to provide a contactless measurement of the membrane movement using the capacitance variations when the membrane is moving.

The special technical feature of invention 4 is to provide an optimized membrane in a sensor for a photo acoustic detector.

The single general concept of the present application is the contactless measurement of a membrane movement.

However, this concept is well-known from the prior art since EP 0389071 discloses a silicon diaphragm pressure transducer. The transducer includes a device having a pair of spaced apart conductive plates defining capacitor plates, and a flexible diaphragm or membrane. A first capacitance exists between the first capacitor plate and the diaphragm. In like manner, a second capacitance exists between the second capacitor plate and the diaphragm. When the diaphragm deflects due to a change in pressure, the capacitances change as well.

Since the concept is known, it cannot be inventive. Hence, there is no single general inventive concept in the sense of Rule 13.1 PCT.

No other features can be distinguished which can be considered as same or corresponding special technical features in the sense of Rule 13.2 PCT.

Thus, the application lacks unity of invention.

INTERNATIONAL SEARCH REPORT

Information on patent family members

International application No.

24/12/2003

PCT/FI 2003/000684

EP	0389071	A2	26/09/1990	DE	69015670 D,T	18/05/1995
				DE	69032583 D,T	07/01/1999
				DE	69033664 D,T	10/05/2001
				EP	0631122 A,B	28/12/1994
				EP	0854358 A,B	22/07/1998
				JP	2290524 A	30/11/1990
				JP	2782546 B	06/08/1998
				US	4996627 A	26/02/1991
				US	5048165 A	17/09/1991

US	6222190	B1	24/04/2001	AT	235676 T	15/04/2003
				AU	3954897 A	14/04/1998
				DE	69720242 D,T	08/01/2004
				DK	939886 T	10/06/2003
				EP	0939886 A,B	08/09/1999
				SE	0939886 T3	
				NO	301854 B	15/12/1997
				NO	963924 D	00/00/0000
				WO	9812522 A	26/03/1998

US	6474168	B1	05/11/2002	AT	232294 T	15/02/2003
				AU	1788799 A	28/06/1999
				DE	69811270 D	00/00/0000
				EP	1034415 A,B	13/09/2000
				NO	308228 B	14/08/2000
				NO	975447 A	27/05/1999
				WO	9930122 A	17/06/1999

US	4557603	A	10/12/1985	AT	38288 T	15/11/1988
				AT	67594 T	15/10/1991
				DE	3279158 D	00/00/0000
				DE	3280358 A	24/10/1991
				EP	0072821 A,B	02/03/1983
				SE	0072821 T3	
				EP	0277662 A,B	10/08/1988
				SE	0277662 T3	
				JP	58500140 T	20/01/1983
				WO	8202950 A	02/09/1982

US	6082178	A	04/07/2000	AT	196197 T	15/09/2000
				AU	4733496 A	27/08/1996
				DE	69610225 D,T	04/01/2001
				EP	0871860 A,B	21/10/1998
				NO	300078 B	01/04/1997
				NO	950505 A	12/08/1996
				WO	9624831 A	15/08/1996

US	4355234	A	19/10/1982	CA	1164248 A	27/03/1984
				JP	57079438 A	18/05/1982